# Mini motion sensor - PIR 2

mini motion sensor without twilight function  Mini Motion Sensor PIR 2



**Description:**
Mini Motion sensor for connecting LED 24 V Lights, Connection cable 0,2 m with LED 24 plug, Switching cable 0,2 m with 11-way distributor, Sensor cable 1,4 m, Recessed installation of the Sensors for 20 mm Drill hole, Run-on time of 10 Seconds to 3 Minuten adjustable, Erfassungswinkel 80°, Detection range 2,5 m with Montagehöhe of 1-2 m.

**Connection:** LED-Trafo DC 24V
**Light colour:** N/A
**Energy efficiency class:** N/A
**Symbols:** IP20, SK III
**Weight:** 0,07 kg

Drilling hole



13mm

**Special features:**

- 0,2 m LED 24 plug / 0,2 m with 11-way distributor/ Sensor 1,4 m
- Protection class 3
- PIR 1: 220–240 V / 50–60 Hz // PIR 2-4: 24 V DC
- Einstellbare Run-on time: 10 sek. to 3 min. (PIR 3+4: 3 min.)
- LED Transformer DC 24 V
- Connector system: LED 24
- Protection rating: IP20
- PIR 1S: The Motion sensor is on the primary side between Transformer and Socket outlet connected (max. 300 W)
- PIR 2S: The Motion sensor is sekundärseitig between LED 24 V Light and LED 24 V Transformer connected (max. 120 W)
- PIR 3: The Motion sensor is sekundärseitig between LED 24 V Light and LED 24 V Transformer connected (max. 120 W). It can Up to 4 Sensor heads on A Motion sensor paired are. Per Sensor head can Up to 3 Motion sensor paired are. Range 11 m
- PIR 4: The Motion sensor can in the Configurator selected are and is vor the Tape into the Profil gesetzt (max. 60 W)

**Order number:**
21703230201

limited availability

## available versions

Choose from the options below. The currently selected one is highlighted in color.

| article number | description | Gehäusefarbe |
|---|---|---|
| 21703230201 | Mini Motion Sensor PIR 2 | Anodized aluminum |