Mini motion sensor - PIR 1

IP 20

mini motion sensor without twilight function Mini Motion Sensor PIR 1



Description:
Mini Motion sensor for connecting Lights-Control gear the Protection class II, Connection cable 2 m with Euro plug, Switching cable 0,3 m with Euro coupling, Sensor cable 1,4 m, Recessed installation of the Sensors for 20 mm Drill hole, Run-on time of 10 Seconds to 3 Minuten adjustable, Erfassungswinkel 80°, Detection range 2,5 m with Montagehöhe of 1-2 m.

Connection:	220 - 240V / 50 - 60Hz
Light colour:	N/A
Energy efficiency class:	N/A
Symbols:	IP20, SK III
Weight:	0,17 kg

Drilling hole



13mm

Special features:

- 2 m Euro plug / 0,15 m Euro coupling / Sensor 1,4 m
- Protection class 2
- PIR 1: 220–240 V / 50–60 Hz // PIR 2-4: 24 V DC
- Einstellbare Run-on time: 10 sek. to 3 min. (PIR 3+4: 3 min.)
- Protection rating: IP20
- PIR 1S: The Motion sensor is on the primary side between Transformer and Socket outlet connected (max. 300 W)
- PIR 2S: The Motion sensor is sekundärseitig between LED 24 V Light and LED 24 V Transformer connected (max. 120 W)
- PIR 3: The Motion sensor is sekundärseitig between LED 24 V Light and LED 24 V Transformer connected (max. 120 W). It can Up to 4 Sensor heads on A Motion sensor paired are. Per Sensor head can Up to 3 Motion sensor paired are. Range 11 m
- PIR 4: The Motion sensor can in the Configurator selected are and is vor the Tape into the Profil gesetzt (max. 60 W)

Order number:
21703230101

limited availability

HERA LED WARRANTY 5 YEARS

available versions

Choose from the options below. The currently selected one is highlighted in color.

article number	description	Gehäusefarbe
21703230101	Mini Motion Sensor PIR 1	Anodized aluminum